

Gauge invariant nonlinear electric transport in mesoscopic conductors

T. Christen¹⁾ and M. Büttiker^{1),2)}

1) Département de physique théorique, Université de Genève, 24 Quai Ernest-Ansermet

CH-1211 Genève, Switzerland

2) Institute of Theoretical Physics, University of California

Santa Barbara, Ca 93106-4030 USA

Abstract

We use the scattering approach to investigate the nonlinear current-voltage characteristic of mesoscopic conductors. We discuss the leading nonlinearity by taking into account the self-consistent nonequilibrium potential. We emphasize conservation of the overall charge and current which are connected to the invariance under a global voltage shift (gauge invariance). As examples, we discuss the rectification coefficient of a quantum point contact and the nonlinear current-voltage characteristic of a resonant level in a double barrier structure.

PACS numbers: 72.20.Ht, 73.40.Ei, 73.40.Gk, 73.50.Fq

Introduction - The scattering approach is widely used to describe electric transport of phase-coherent mesoscopic conductors in the linear response regime [1]. Nonlinear effects of interest are asymmetric current-voltage characteristics and rectification [2], the evolution of half-integer conductance plateaus [3], the breakdown of conductance quantization [4], and negative differential conductance and hysteresis [5]. In general, in the nonlinear regime inelastic processes which destroy the phase coherence can play an important role. Below, however, we emphasize phase-coherent nonlinear transport. The nonequilibrium state is determined by the potential generated by the nonequilibrium charges piled up in a biased conductor. A reasonable theory of nonlinear electric transport has to take into account this potential self-consistently. Most importantly, for a mesoscopic sample there exists a Gauss volume which encloses the mesoscopic conductor and nearby gates (capacitors) such that the electric flux through the surface of this volume vanishes [6]. Thus the total charge inside this volume is conserved. Consequently, the I-V-characteristic is gauge invariant: it is invariant under a global potential shift and depends only on the differences of the voltages applied to the contacts of the sample or nearby capacitors [6]. Nonlinearities in tunnel contacts have already been addressed in an early paper by Frenkel [7]. The necessity to consider the self-consistent potential has been emphasized by Landauer [8]. Nevertheless, many works on nonlinear transport [3,9] consider only the non-interacting case or consider interactions which are not gauge invariant. An exception is, e.g., a work by Kluksdahl et al. [5] which provides a self-consistent numeric treatment of a tunneling barrier with the help of Wigner functions.

In this Letter we present a self-consistent, gauge-invariant theory of weakly nonlinear transport using the scattering approach. A gauge invariant theory of linear ac-conductance is the subject of Refs. [6,10–12]. The discussion of non-linear transport presented here is based on similar concepts. We can illustrate the main points using an effective Hartree approach to treat the effects of the long range Coulomb interaction. The Hartree approach has a wide range of applicability but excludes single-charge effects [13].

The leading nonlinearity - Consider a mesoscopic conductor which is connected via con-

tacts $\alpha = 1, \dots, N$ to N electron reservoirs. We allow that some parts of the conductor are disconnected from other parts in order to include into the formalism the presence of nearby gates (capacitors). The transport properties are described by the scattering-matrix elements $s_{\alpha\beta nm}$ which relate the out-going current amplitude in channel n at contact α to the incident current amplitude in channel m at contact β . We denote by $\mathbf{s}_{\alpha\beta}$ the scattering matrix with rows and lines associated with the channels n and m [14]. The scattering matrix is a function of the energy E of the wave and is a functional of the electric potential $U(x, \{V_\gamma\})$ in the conductor. This potential in turn depends on the shifts eV_γ of the electrochemical potentials μ_γ of the reservoirs away from the equilibrium state associated with μ^{eq} . Hence, the determination of the scattering matrix $\mathbf{s}_{\alpha\beta}(E, \{V_\gamma\})$ as a function of the energy and the voltage shifts in the reservoirs defines a formidable self-consistent problem. Once this scattering matrix is found we can calculate the current through contact α [14]

$$I_\alpha = \frac{2e}{h} \sum_{\beta=1}^N \int dE f(E - E_F - eV_\beta) A_{\alpha\beta}(E, \{V_\gamma\}) \quad (1)$$

where $f(z) = (1 + \exp(z/k_B T))^{-1}$ is the Fermi function of a reservoir at temperature T , and $A_{\alpha\beta}(E, \{V_\gamma\}) = \text{Tr}[\mathbf{1}_\alpha \delta_{\alpha\beta} - \mathbf{s}_{\alpha\beta}^\dagger(E, \{V_\gamma\}) \mathbf{s}_{\alpha\beta}(E, \{V_\gamma\})]$ are the *screened* (negative) transmission functions. To discuss weakly nonlinear transport, we write for the current

$$I_\alpha = \sum_{\beta} G_{\alpha\beta} V_\beta + \sum_{\beta\gamma} G_{\alpha\beta\gamma} V_\beta V_\gamma + \dots \quad (2)$$

The coefficients $G_{\alpha\beta}$ and $G_{\alpha\beta\gamma}$ are obtained from an expansion of Eq. (1) with respect to the voltages V_α . One obtains for the linear conductance the well-known expression $G_{\alpha\beta} = (2e^2/h) \int dE (-\partial_E f) A_{\alpha\beta}$, where the $A_{\alpha\beta}$ are taken at $V_1 = \dots = V_N = 0$. An expansion of Eq. (1) up to $\mathcal{O}(V_\beta V_\gamma)$ yields

$$G_{\alpha\beta\gamma} = \frac{e^2}{h} \int dE (-\partial_E f) (2\partial_{V_\gamma} A_{\alpha\beta} + e\partial_E A_{\alpha\beta} \delta_{\beta\gamma}) \quad (3)$$

Conservation of the total charge (gauge invariance) implies that the currents are conserved [6,10] and that the currents be independent of a global voltage shift W : $V_\alpha \rightarrow V_\alpha + W$. These conditions imply the sum rules [11] $\sum_\alpha G_{\alpha\beta} = \sum_\beta G_{\alpha\beta} = 0$. Similarly, the coefficients of the second-order nonlinearity must obey

$$\sum_{\alpha} G_{\alpha\beta\gamma} = \sum_{\gamma} (G_{\alpha\beta\gamma} + G_{\alpha\gamma\beta}) = 0 \quad . \quad (4)$$

The sum rules also follow from the unitarity of the scattering matrix, i.e. $\sum_{\alpha} A_{\alpha\beta} = \sum_{\beta} A_{\alpha\beta} = 0$, and from the gauge invariance condition $e\partial_E A_{\alpha\beta} + \sum_{\gamma} \partial_{V_{\gamma}} A_{\alpha\beta} = 0$.

To determine the derivatives $\partial_{V_{\gamma}} A_{\alpha\beta}$ we recall that the $A_{\alpha\beta}$ are functionals of the electric potential $U(x, \{V_{\gamma}\})$. Within linear response theory the potential variation $\Delta U(x) = U(x) - U_{eq}(x)$ away from equilibrium is determined by the *characteristic potentials* $u_{\gamma}(x) = (\partial U(x)/\partial V_{\gamma})_{eq}$. To derive the characteristic potentials we introduce the *injectivities* $dn(x, \alpha)/dE = -(1/4\pi i) \sum_{\beta} [\mathbf{s}_{\beta\alpha}^{\dagger} (\delta \mathbf{s}_{\beta\alpha}/e\delta U(x)) - (\delta \mathbf{s}_{\beta\alpha}^{\dagger}/e\delta U(x)) \mathbf{s}_{\beta\alpha}]$. The injectivity which is related to a dwell-time [10,15] is a partial local density of states, i.e. the sum over all contacts α gives the local density of states $dn(x)/dE$. Variations eV_{α} of the electrochemical potentials μ_{α} in the contacts at fixed electric potential $U_{eq}(x)$ in the conductor induce a charge density $q^{(1)}(x) = e^2 \sum_{\alpha} (dn(x, \alpha)/dE) V_{\alpha}$. In general, however, the electric potential changes by $\Delta U(x)$ which induces an additional charge density $q^{(2)}(x) = -e^2 \int \Pi(x, y) \Delta U(y) d^3y$, where $\Pi(x, y)$ is the Lindhard polarization function. Inserting the total nonequilibrium charge $q^{(1)} + q^{(2)}$ and the potential variation $\Delta U = \sum u_{\alpha} V_{\alpha}$ into the Poisson equation yields for the characteristic potentials an equation with a nonlocal screening term [6]

$$-\Delta u_{\alpha}(x) + 4\pi e^2 \int d^3y \Pi(x, y) u_{\alpha}(y) = 4\pi e^2 \frac{dn(x, \alpha)}{dE} \quad . \quad (5)$$

For simplicity, the dielectric constant is to be unity. The derivative $\partial_{V_{\gamma}} A_{\alpha\beta}$ can be expressed in terms of the functional derivative $\delta A_{\alpha\beta}/\delta U(x)$ and the characteristic potentials, which yields for Eq. (3)

$$G_{\alpha\beta\gamma} = \frac{e^3}{h} \int dE (-\partial_E f) \int d^3x \frac{\delta A_{\alpha\beta}}{e\delta U(x)} (2u_{\gamma}(x) - \delta_{\beta\gamma}) \quad . \quad (6)$$

Discrete potential model - We can obtain analytical results by using a convenient coarse graining model for the conductors [12]. We discretize the conductor by decomposing it into M regions where the electrostatic potential and the charge density are assumed to be constant. Space dependent quantities are written as M -dimensional vectors or as $M \times M$ -matrices. For example, the electrostatic potential variation $\Delta U(x)$ becomes a vector $\Delta \mathbf{U} =$

$(\Delta U_1, \dots, \Delta U_M)$, where ΔU_k denotes the electrostatic potential shift in region k . We write the injectivities as vectors $\mathbf{D}_\alpha = e^2(dN_{1\alpha}/dE, \dots, dN_{M\alpha}/dE)$ where we multiplied by e^2 for later convenience. The functional derivative with respect to the potential $U(x)$ is replaced by the gradient $\nabla_{\mathbf{U}}$, and the polarization function is a matrix $\mathbf{\Pi}$. We introduce a geometric capacitance matrix $\mathbf{C}$ associated with these regions and which is calculated from the Poisson equation. The nonequilibrium charge distribution is $\mathbf{q} = \mathbf{C}\Delta\mathbf{U} = \sum_\beta \mathbf{D}_\beta V_\beta - \mathbf{\Pi}\Delta\mathbf{U}$ which yields for the characteristic potentials $\mathbf{u}_\beta = (\mathbf{\Pi} + \mathbf{C})^{-1}\mathbf{D}_\beta$. Hence, Eq. (6) becomes

$$G_{\alpha\beta\gamma} = \frac{e^2}{h} \int dE (-\partial_E f) (2\nabla_{\mathbf{U}} A_{\alpha\beta} (\mathbf{\Pi} + \mathbf{C})^{-1}\mathbf{D}_\gamma - e\delta_{\beta\gamma} \partial_E A_{\alpha\beta}) . \quad (7)$$

We mention that the charge q_k in region k can be written in terms of an electrochemical capacitance matrix [12], $q_k = \sum_\beta C_{k\beta}^\mu V_\beta$ where $C_{k\beta}^\mu = \sum_l C_{kl} u_{l\beta}$.

In the following we investigate two-terminal devices. Due to gauge invariance, the current $I_1 = -I_2 = G_{11}\Delta V + G_{111}(\Delta V)^2 + \dots$ depends only on the voltage difference $\Delta V = V_1 - V_2$. The second-order nonlinearity is thus determined by the single rectification coefficient G_{111} .

Rectification of a quantum point contact - We follow closely Ref. [12] and discretize the quantum point contact (QPC) by defining to the left and to the right of the constriction two regions Ω_1 and Ω_2 with sizes of the order of the screening length. We assume zero temperature and take all quantities at the Fermi energy. A voltage difference across the QPC induces a dipole consisting of charges q_1 and $q_2 = -q_1$ which reside in Ω_1 and Ω_2 , respectively. Each occupied subband j contributes with a transmission probability T^j to the total transmission function $\mathcal{T} = \sum_j T^j$. Due to charge conservation, the geometrical capacitance matrix has the specific form $C_{kl} = (-1)^{k+l}C$. Assuming a barrier potential of the constriction which allows a WKB approximation, we can neglect nonlocalities and write $\Pi_{kl} = D_k \delta_{kl}$. With each channel j one can associate a density of states D_k^j in region Ω_k , and it must hold $D_k = \sum_j D_k^j = \sum_\alpha D_{k\alpha}$. For a voltage variation V_1 , channel j injects from contact 1 into Ω_2 a charge $D_2^j(T^j/2)V_1$ and into Ω_1 a charge $D_1^j(1 - T^j/2)V_1$. A sum over all channels j yields the injectivity $\mathbf{D}_1$ of contact 1 with the components $D_{11} = D_1(1 - T_1/2)$ and $D_{21} = D_2 T_2/2$. Here, $T_k = D_k^{-1} \sum_j D_k^j T^j$ are averaged transmission probabilities. We

obtain for the characteristic potentials $u_{11} = 1 - T_1/2 - C^\mu/D_1$ and $u_{21} = T_2/2 + C^\mu/D_2$, where the electrochemical capacitance is given by $C^\mu = R/(C^{-1} + D_1^{-1} + D_2^{-1})$ and where we introduced the average reflection probability $R = 1 - (T_1 + T_2)/2$. The rectification coefficient becomes thus

$$G_{111} = \frac{e^2}{h} \left(\frac{C^\mu}{C} (\partial_{U_1} \mathcal{T} - \partial_{U_2} \mathcal{T}) + [C^\mu (D_2^{-1} - D_1^{-1}) - \frac{1}{2} (T_1 - T_2)] e \partial_E \mathcal{T} \right). \quad (8)$$

As one expects, G_{111} vanishes for a symmetric barrier. Asymmetries can be due to differences of D_k , T_k , and $\partial_{U_k} \mathcal{T}$ for different k . Consider a single-channel conductor where $T_1 - T_2$ vanishes and which can be seen as a model for a one-dimensional conductor with an impurity. In the limit $C \ll D_k$, charges are screened and the rectification coefficient is $G_{111} = (e^2/h) R (\partial_{U_1} \mathcal{T} - \partial_{U_2} \mathcal{T})$. On the other hand, in the limit $D_k \ll C$, Eq. (8) gives $G_{111} = (e^3/h) (D_2 - D_1) R \partial_E T / (D_1 + D_2)$ which is proportional to the asymmetry of the density of states. Clearly, with a discretization by more than two regions, an additional source of asymmetry can result from asymmetric electric screening (unequal capacitance coefficients).

Resonant tunneling barrier - To model the resonant tunneling barrier, we consider three discrete potential regions denoted by indices 0, 1, and 2 which correspond to the well, the left side of the barriers, and the right side of the barriers, respectively. We assume fully screened charges. Consider a single resonant level with energy $E_r + eU_0$ which is clearly separated from other resonant levels, from the band bottoms, and from the left and right barrier tops. The linear conductance of such a structure is given by $G_{11} = (2e^2/h)T$ where T is the transmission probability of the double barrier structure. Linear response is only valid if the bias $|e\Delta V|$ is much smaller than the width Γ of the resonance. To find the nonlinear characteristic, we restrict ourselves to near resonant conditions where the transmission probability can be approximated by the Breit-Wigner formula $T(E, U) = \Gamma_1 \Gamma_2 / |\Delta|^2$ with $|\Delta|^2 = (E - E_r - eU_0)^2 + \Gamma^2/4$. In this range the nonlinearity is solely due to the resonance. In particular, we assume that Γ_1 and Γ_2 , and thus the width $\Gamma = \Gamma_1 + \Gamma_2$ of the resonant level and the asymmetry, $\Delta\Gamma = \Gamma_1 - \Gamma_2$, are constant. The injectivities are [11]

$D_{0\alpha}(E, U_0) = (e^2/2\pi)\Gamma_\alpha/|\Delta|^2$. The relation between the electrostatic potential shift ΔU_0 and the voltage shifts $V_\alpha = (\mu_\alpha - \mu^{eq})/e$ ($\equiv \Delta U_\alpha$) is obtained from the charge-neutrality condition

$$\int_{-\infty}^{\mu_1} D_{01}(E, U_0) dE + \int_{-\infty}^{\mu_2} D_{02}(E, U_0) dE - \int_{-\infty}^{\mu^{eq}} D_0(E, U_0^{eq}) dE \equiv 0, \quad (9)$$

which can be integrated analytically. Eq. (9) determines $W = \Delta U_0 - (V_1 + V_2)/2$ which depends on ΔV only. Equation (1) yields for the current $I \equiv I_1 = -I_2$

$$I = \frac{4e}{h} \frac{\Gamma_1 \Gamma_2}{\Gamma} (\arctan[2(\Delta E - e(W - \Delta V/2))/\Gamma] - \arctan[2(\Delta E - e(W + \Delta V/2))/\Gamma]) , \quad (10)$$

where $\Delta E = \mu_{eq} - (eU_0^{eq} + E_r)$ is the equilibrium distance between the Fermi energy and the resonance. Without considering the self-consistent shift ΔU_0 one would get a wrong result which is not gauge invariant. The current given by Eq. (10) saturates at a maximum value proportional to $\pi/2 - \arctan(2\Delta E/\Gamma)$. The conduction is optimal for $\Delta E = 0$ and $\Gamma_1 = \Gamma_2$ when $I = 2(e/h)\Gamma \arctan(e\Delta V/\Gamma)$. In Fig. 1 we have plotted the characteristic as a function for an asymmetry $\Delta\Gamma/\Gamma = -1/3$ and for various values of ΔE . For the case of complete screening considered here, the resonant level floats up or down to keep the charge in the well constant. An expansion of the current yields $G_{111} = -(e^3/h)(\Delta\Gamma/\Gamma)\partial_E T$ which is in accordance with (7) and with Ref. [12] (thin dotted lines in Fig. 1). The case of incomplete screening can similarly be treated with our approach. In this case, at large voltages, the resonance can eventually fall below the conductance band bottom of the injecting reservoir as is known from the semiconductor double barrier structures. In the general case, even an elastically symmetric resonance can be rectifying if the electrical screening is asymmetric.

Conclusion - In this work we have emphasized that a reasonable theory of nonlinear electrical transport in mesoscopic conductors requires a self-consistent treatment of the long-range Coulomb interactions which insures gauge invariant results. We showed that the scattering approach to mesoscopic conduction provides an appropriate method if one introduces screened scattering matrices which depend on the self-consistent potential.

Acknowledgement This work has been supported by the Swiss National Science Foundation. For M.B. part of this work was supported by the US National Science Foundation under grant PHY94-07194.

REFERENCES

- [1] S. Datta, *Electronic Transport in Mesoscopic Systems* (Cambridge University Press, 1995); C. W. J. Beenakker and H. van Houten, Solid State Phys. **44**, 1 (1991); Y. Imry, in *Directions in Condensed Matter Physics*, Vol. 1, edited by G. Grinstein and G. Mazenko (World Scientific, Singapore, 1986) p.101.
- [2] R. Taboryski et al., Phys. Rev. B **49**, 7813 (1994); S. Verghese et al., Phys. Rev. B **52**, 14834 (1995).
- [3] L. I. Glazman and A. V. Khaetskii, Europhys. Lett. **9**, 263 (1989); N. K. Patel et al., J. Phys.: Condens. Matter **2**, 7247 (1990); Phys. Rev. B **44**, 13549 (1991).
- [4] L. P. Kouwenhoven et al., Phys. Rev. B **39**, 8040 (1989).
- [5] N. C. Kluksdahl et al., Phys. Rev. B **39**, 7720 (1989)
- [6] M. Büttiker, J. Phys.: Condens. Matter **5**, 9361 (1993).
- [7] J. Frenkel, Phys. Rev. **36**, 1604 (1930).
- [8] R. Landauer, in *Nonlinearity in Condensed Matter*, edited by A. R. Bishop et al. (Springer, Berlin, 1987) p.2.
- [9] B. L. Al'tshuler and D. E. Khmel'nitskii, JETP Lett. **42**, 359 (1985); E. Castaño and G. Kirczenow, Phys. Rev. B **41**, 3874 (1990); I. E. Aronov, A. M. Zagoskin, and M. Jonson, Solid State Commun. **95**, 647 (1995); A. M. Zagoskin and R. I. Shekhter, Phys. Rev. B **50**, 4909 (1994).
- [10] M. Büttiker and T. Christen, to appear in *Quantum Transport in Semiconductor Sub-micron Structures*, edited by B. Kramer, (Dordrecht, Kluwer, 1996).
- [11] M. Büttiker, A. Prêtre, and H. Thomas, Phys. Rev. Lett. **70**, 4114 (1993); Z. Phys. B **94**, 133 (1994).
- [12] T. Christen and M. Büttiker, unpublished.

- [13] C. Bruder, R. Fazio, and H. Schöller, Phys. Rev. Lett. **76**, 114 (1996), gauge invariance is investigated by C. A. Stafford (unpublished).
- [14] M. Büttiker, Phys. Rev. B **46**, 12485 (1992).
- [15] V. Gasparian, T. Christen, and M. Büttiker, unpublished.

FIGURES

FIG. 1. Current-voltage characteristic of a single level of the resonant tunneling barrier; $\Gamma_1 = 0.5meV$, $\Gamma_2 = 1meV$, $\Delta E = 0$ (solid), $\Delta E = -\Gamma$ (dashed); $\Delta E = -2\Gamma$ (dotted). Thin dotted lines indicate the quadratic approximation.

